




Design: O/M  
Ceiling-recessed luminaire made of aluminium die-cast.  
Recessing system with spring clips.


LED CRI>90 / >50.000h, L80/B10  
3-step MacAdam / Power supply not included  
IP44 | 300mA / 150mA



|  |            |                |                |
|--|------------|----------------|----------------|
| <br>LED | 2700K      |                |                |
|  |            | Light Source   | Luminaire      |
|  | Power      | 10W / 5W       | 10W / 5W       |
|  | Flux       | 1505lm / 755lm | 1190lm / 595lm |
|  | Efficiency | 151lm/W        | 119lm/W        |
|  | LOR        | -              | 79%            |
|  |            | UGR            | <10            |



Beam angle  
Spot 20°

Application  


Weight  
0.37Kg



Ø90



#### Finishes

- .04 Matt White
- .05 Matt Black

#### Mandatory

**59109** Driver On/Off [300mA]

147x43x30mm

**59108** Driver On/Off [150mA]

147x43x30mm

**59111** Driver DALI [300mA]

144x30x21mm

**59110** Driver DALI [150mA]

144x30x21mm

**59113** Driver PhaseCut [300mA]

102x51x30mm

**59112** Driver PhaseCut [150mA]

102x49x29mm

**59115** Driver 1-10V [300mA]

130x30x20mm

**59114** Driver 1-10V [150mA]

130x30x20mm

The cutout dimensions are for plasterboard ceilings. For other type of material please contact: [support@om-light.com](mailto:support@om-light.com)

The 5-year guarantee applies only when the luminaire and driver are supplied together.


#### Data according to regulations

2019/2020/EU supplemented by 2021/341 [2019/2015/EU

supplemented by 2021/340/EU Energy Consumption Labelling


Ordinance. This product contains a light source of efficiency class E

Model Identifier BXRE-27G10FB-C-83




Go

Driver On/Off [1 luminaire] 59109



Driver On/Off for Go ø100  
[300mA]  
230Vac | 50/60Hz | Class II


|        |          |
|--------|----------|
| Weight | Finishes |
| 0,08Kg | .99      |



Go

Driver On/Off [1 luminaire]


59108



Driver On/Off for Go ø100  
[150mA]  
230Vac | 50/60Hz | Class II


Weight  
0,08Kg

Finishes  
.99



Go


Driver DALI [1 luminaire] 59111



Driver DALI for Go ø100 [300mA]  
230Vac | 50/60Hz | Class II


Weight  
0,08Kg

Finishes  
.99




Go

Driver DALI [1 luminaire] 59110




Driver DALI for Go ø100 [150mA]  
230Vac | 50/60Hz | Class II

|        |          |
|--------|----------|
| Weight | Finishes |
| 0,08Kg | .99      |




Driver PhaseCut [1 luminaire] 59113




Driver PhaseCut for Go ø100  
[300mA]  
230Vac | 50/60Hz | Class II

|        |          |
|--------|----------|
| Weight | Finishes |
| 0,09Kg | .99      |



Go

Driver PhaseCut [1 luminaire] 59112




Driver PhaseCut for Go ø100  
[150mA]  
230Vac | 50/60Hz | Class II

Weight  
0,13Kg


Finishes  
.99






Go

Driver 1-10V [1 luminaire] 59115



Driver 1-10V for Go ø100 [300mA]  
230Vac | 50/60Hz | Class II


|        |          |
|--------|----------|
| Weight | Finishes |
| 0,07Kg | .99      |



Go

Driver 1-10V [1 luminaire]

59114



Driver 1-10V for Go ø100 [150mA]  
230Vac | 50/60Hz | Class II

Weight  
0,07Kg

Finishes  
.99