

10W / 5W / 1215lm / 610lm / 3500K / On/Off
/ Spot 20° / ø100mm


64766



Design: O/M
Ceiling-recessed luminaire made of aluminium die-cast.
Recessing system with spring clips.

LED CRI>90 / >50.000h, L80/B10
3-step MacAdam / Power supply not included
IP44 | 300mA / 150mA



 3500K	Light Source	Luminaire
Power	10W / 5W	10W / 5W
Flux	1540lm / 770lm	1215lm / 610lm
Efficiency	154lm/W	122lm/W
LOR	-	79%
UGR	-	<10



Beam angle
Spot 20°

Application



Weight
0.37Kg



Ø90



Finishes

- .04 Matt White
- .05 Matt Black

Mandatory

59109 Driver On/Off [300mA]

147x43x30mm

59108 Driver On/Off [150mA]

147x43x30mm

59111 Driver DALI [300mA]

144x30x21mm

59110 Driver DALI [150mA]

144x30x21mm

59113 Driver PhaseCut [300mA]

102x51x30mm

59112 Driver PhaseCut [150mA]

102x49x29mm

59115 Driver 1-10V [300mA]

130x30x20mm

59114 Driver 1-10V [150mA]


130x30x20mm

The cutout dimensions are for plasterboard ceilings. For other type of material please contact: support@om-light.com

The 5-year guarantee applies only when the luminaire and driver are supplied together.

Data according to regulations


2019/2020/EU supplemented by 2021/341 [2019/2015/EU supplemented by 2021/340/EU Energy Consumption Labelling Ordinance. This product contains a light source of efficiency class E Model Identifier BXRE-35G10FB-C-83



Go

Driver On/Off [1 luminaire]


59109



Driver On/Off for Go ø100
[300mA]
230Vac | 50/60Hz | Class II


Weight
0,08Kg

Finishes
.99




Go

Driver On/Off [1 luminaire] 59108




Driver On/Off for Go ø100
[150mA]
230Vac | 50/60Hz | Class II

Weight	Finishes
0,08Kg	.99




Go

Driver DALI [1 luminaire] 59111




Driver DALI for Go ø100 [300mA]
230Vac | 50/60Hz | Class II

Weight	Finishes
0,08Kg	.99




Go

Driver DALI [1 luminaire] 59110




Driver DALI for Go ø100 [150mA]
230Vac | 50/60Hz | Class II

Weight	Finishes
0,08Kg	.99




Driver PhaseCut [1 luminaire] 59113




Driver PhaseCut for Go ø100
[300mA]
230Vac | 50/60Hz | Class II

Weight	Finishes
0,09Kg	.99




Go

Driver PhaseCut [1 luminaire] 59112



Driver PhaseCut for Go ø100
[150mA]
230Vac | 50/60Hz | Class II


Weight	Finishes
0,13Kg	.99



Go

Driver 1-10V [1 luminaire]


59115



Driver 1-10V for Go ø100 [300mA]
230Vac | 50/60Hz | Class II

Weight
0,07Kg


Finishes
.99



Go

Driver 1-10V [1 luminaire]

59114



Driver 1-10V for Go ø100 [150mA]
230Vac | 50/60Hz | Class II

Weight
0,07Kg

Finishes
.99