

32W / 1450lm / 3000K / DALI / Wallwasher /  
1200mm

61250



#### Structure

- 1 Profile
- 2 End caps
- 3 Fitting accessories
- 4 Profile coupling

#### Modules

- A Uw modules

Design: O/M + Bartenbach GmbH  
LED light source with excellent colour consistency  
and long operation lifespan.  
Asymmetrical aluminium reflector.

LED CRI>90 / >50.000h, L80/B10  
2-step MacAdam / power supply included.  
IP20 | 230Vac | 50/60Hz



LED	3000K	Light Source	Luminaire
Power		32W	38W
Flux		3200lm	1450lm
Efficiency		100lm/W	38lm/W
LOR		-	45%
UGR		-	-



Beam angle  
Wallwasher

#### Application



Weight  
2Kg



#### Finishes

- .01 White / RAL 9010
- .02 Black / RAL 9005
- .10 Anodised aluminium

For the specific supply of "DALI 2" drivers, please contact:  
support@om-light.com  
Choose the length and layout of the system exactly as you want it, to  
model the right lighting functions for different tasks. For further  
information please contact: support@om-light.com

