

16W / 1340lm / 3000K / DALI / Diffuse /  
1119mm

61358

Design: O/M

LED light source with good colour consistency and long operation lifespan.

LED CRI>80 / >50.000h, L80/B10 / 3-step MacAdam  
Power supply included.  
IP20 | 230Vac | 50/60Hz



### Structure

- 1 Profile
- 2 End caps
- 3 Fitting accessories
- 4 Profile coupling

### Diffuser

- A Polycarbonate frost diffuser

### Light Source

- B LED Modules

LED	3000K	Light Source	Luminaire
Power		16W	19,5W
Flux		2860lm	1340lm
Efficiency		179lm/W	69lm/W
LOR		-	47%
UGR		-	<25



Beam angle  
Diffuse

Application



Weight  
0,57Kg



### Finishes

For the specific supply of "DALI 2" drivers, please contact:  
[support@om-light.com](mailto:support@om-light.com)

Choose the length and layout of the system exactly as you want it, to model the right lighting functions for different tasks. For further information please contact: [support@om-light.com](mailto:support@om-light.com)

### Data according to regulations

2019/2020/EU supplemented by 2021/341 | 2019/2015/EU supplemented by 2021/340/EU Energy Consumption Labelling Ordinance. This product contains light sources of efficiency class C  
Model Identifier 89603216