

34W / 3300lm / 4000K / On/Off / Diffuse /
1399mm

61377

Design: O/M
LED light source with good colour consistency and
long operation lifespan.

LED CRI>80 / >50.000h, L80/B10 / 3-step MacAdam
Power supply included.
IP20 | 230Vac | 50/60Hz




- | | |
|-----------------------|--------------------------------|
| Structure | Diffuser |
| 1 Profile | A Polycarbonate frost diffuser |
| 2 End caps | |
| 3 Fitting accessories | Light Source |
| 4 Profile coupling | B LED Modules |

LED	4000K	Light Source	Luminaire
Power		34W	40W
Flux		6500lm	3300lm
Efficiency		191lm/W	83lm/W
LOR		-	51%
UGR		-	<25



Beam angle
Diffuse



Weight
0,58Kg



Finishes
Choose the length and layout of the system exactly as you want it, to
model the right lighting functions for different tasks. For further
information please contact: support@om-light.com

